



**HUNT ENGINEERING**  
Chestnut Court, Burton Row,  
Brent Knoll, Somerset, TA9 4BP, UK  
Tel: (+44) (0)1278 760188,  
Fax: (+44) (0)1278 760199,  
Email: sales@hunteng.co.uk  
URL: <http://www.hunteng.co.uk>  
<http://www.hunt-dsp.com>



**‘one of the many tools we have to help us build your system solution’**



### ***HERON-FPGA3 FPGA module with Digital I/O***

- **Xilinx Virtex II FPGA with 1M gates.**
- **FPGA configuration downloaded using the HERON Serial Bus.**
- **Choice of clocking options**
- **90 user defined Digital I/Os**
- **Several serial I/O options possible -- configured by the FPGA.**
- **Connects to all of the HERON FIFOs, UMI and module ID signals**
- **Flash PROM for storage of configuration data**

The HERON-FPGA3 provides a user programmable FPGA element for a HERON system. This can be used to process data flows or as a flexible digital I/O module.

Using the HERON serial bus allows the FPGA to be configured with a standard module configuration, or a custom one provided by the user, or HUNT ENGINEERING. After configuration the module can accept user messages over the HERON serial bus allowing registers etc to be programmed. If a more significant programming change is required a complete new FPGA configuration can be downloaded. The FLASH based configuration PROM can load the configuration data into the FPGA when it is used in an embedded system This PROM can be programmed using the standard JTAG cable available from Xilinx (such as Xilinx Parallel cable 3 or 4).

The Digital I/O has a number of voltage formats such as LVTTTL or LVCMOS defined by the combination of a jumper setting and the configuration downloaded to the FPGA. In addition it is possible for the HERON-FPGA3 to be used as a choice of RS232, RS485 and Differential ECL serial interfaces.


The HERON-FPGA3 can access HERON-FIFOs at a rate of 32 bits per FIFO clock in AND 32 bits per FIFO clock out concurrently. For example with a FIFO clock of 100Mhz this is 400Mbytes/sec in AND 400Mbytes/sec out

The use of a Virtex II XC2V1000fg456-4 part allows clock rates of up to 365Mhz, and also provides hard coded multipliers and extended I/O formats such as Low Voltage Differential Signalling (LVDS)

**NOTE VIRTEX II I/Os are not 5v tolerant! Optional 100R series resistors can be fitted to make inputs 5V tolerant.**

**“Find your system solution at [www.hunteng.co.uk](http://www.hunteng.co.uk)”**

## Block Diagram



Technical Specification	Software	Ordering Information
<p><b>Processor:</b> Virtex II</p> <p><b>Memory:</b> None external to FPGA</p> <p><b>Host Bus:</b> HERON</p> <p><b>Maximum Dimensions:</b> 4.0 inches x 2.5inches x 6.5mm high.</p> <p><b>Power requirements:</b> 5V dependent on FPGA configuration 12V Max: 0A Typ: 0A -12V Max:0A Typ:0A</p> <p><b>FPGA Power Consumption/Dissipation</b> Max Bare FPGA package dissipation: 2.4W</p> <p>From 5V supply : FPGA PSU power can source 7.2W for Virtex II FPGA PSU power can source 8.7W for</p> <p><b>Clocking Speed:</b> Max HERON-FPGA3V 365Mhz</p> <p><b>I/O bandwidth:</b> e.g. HEPC9 400Mb/s in + 400Mb/s out</p>	<p>Xilinx Foundation series tools are required to make a new FPGA configuration. HUNT ENGINEERING provides software to download the FPGA configuration file onto the hardware, plus configuration examples. HUNT ENGINEERING may offer to provide your configuration file for you, but this may be chargeable.</p> <p><b>Applications</b> These fast FPGAs can be used for DSP processing tasks at very high clock rates. Alternatively the HERON-FPGA3 can be used to provide custom digital I/O perhaps combined with signal generation of pre-processing.</p> <p><b>Related Products</b> HEPC9 – PCI Heron Module carrier HERON2-DSP module</p>	<p><b>HERON-FPGA3V</b></p>

HUNT ENGINEERING acknowledges all Trademarks used in this document.  
This document does not form part of a contract, HUNT ENGINEERING reserves the right to change product specifications without notice and to refuse to supply any item detailed on this data sheet  
E&OE.

Distributor details: